

How to set alpha-numeric as Account ID

(KX-TGP series)

No. 06-002

March 3 , 2011

Ver.1.0

Panasonic Corporation

Abstract about this document

This document describe about Supporting alpha-numeric as Account ID on TGP5xx. Some SIP server request alpha-numeric as SIP account ID information for Register, Invite and so on. This document how TGP support and how to set up alpha-numeric value as account information.

Revision history

Date	Version	Revision	Firmware version
Mar. 3, 2011	Ver. 1.0	Initial Release	12.04/22.04 or later

1. Outline

1. “Line ID”

- New parameter, “Line ID” was added.
- It can be handled separately from “Phone Number”.
- “Line ID” can be configured both with WEB and Configuration file.

2. Alphabetic characters can be set in “Line ID”

- “Line ID” could be configured with any random string including alphabetic letters.
- The value range of “Phone Number” is the same as it now is.

3. How to use “Line ID”, “Phone Number”

- The one that the user usually use/see is “Phone Number”.
- “Line ID” is used only in the SIP header through SIP processing.

2. Web setting page with “Line ID”

KX-TGP550T01

Status Network System **VoIP** Telephone Maintenance

Web Port Close

SIP Settings [Line 1]

Phone Number

Phone Number

Line ID

SIP Server

Registrar Server Address

Registrar Server Port [1-65535]

Proxy Server Address

Proxy Server Port [1-65535]

Presence Server Address


Presence Server Port [1-65535]

Outbound Proxy Server

Description	Specifies the unique ID used by the SIP registrar server. Note • When you use characters that are not allowed for [Phone Number], you must specify [Phone Number] and then this setting.
Value Range	Max. 24 characters (except @)
Default Value	Not stored.

Description	Specifies the unique ID used by the SIP registrar server. Note • When you use characters that are not allowed for "PHONE_NUMBER_[1-8]", you must specify "PHONE_NUMBER_[1-8]" and then this setting.
Value Range	Max. 24 characters (consisting of 0-9, *, and #) Note • No other characters are allowed.
Default Value	Not stored.

3. SIP call flow with new parameter set



Phone Number	
Phone Number	9100
Line ID	9100_Alice

Phone Number	
Phone Number	9200
Line ID	9200_Bob

Only Phone number(9100) is displayed on LCD when incoming call from Alice. ("Alice" is not displayed)