Call Transfer Features

(KX-UT670)

No. 25-004

Dec 22, 2011

Ver.1.0

Panasonic Corporation

Abstract about this document

This document describe about Call Transfer Features. There are 2 types of call transfer feature in UT670.

Revision history

Date	Version	Revision	Firmware version
Dec 22, 2011	Ver. 1.0	Initial Release	All versions

Call Transfer Feature

UT670 has 2 types of Call Transfer Feature, A) and B).

- A) Transfer
- B) Blind Transfer

Call Transfer

	Call Transfer Feature	Description	Reference in Operating Instructions
A	Transfer	Transferring after the Destination Answers	 During a call, tap [Transfer] on the [Current] tab. Call the party to whom you want to transfer the call. When the destination party answers, tap [Transfer Complete]. Note In step 1, instead of tapping [Transfer], you can tap a flexible button assigned as a BLF button to call the transfer destination. If On-hook Transfer is enabled at your unit, you can simply go on-hook in step 3 instead of tapping [Transfer Complete]. For details, consult your administrator or dealer. In step 3, instead of tapping [Transfer Complete], you can tap [Swap] to put the transfer destination on hold and talk to the party you are transferring. Tapping [Swap] again returns you to the transfer destination. If the transfer destination does not answer, either tapping [Transfer Cancel] or tapping the DN flexible button for the call on hold (flashing green slowly) returns you to the original call. In step 3, the call will still be transferred even if you go on-hook before the transfer destination answers.

Call Transfer

	Call Transfer Feature	Description	Reference in Operating Instructions
В	Blind transfer	Transferring without Waiting for a Response from the Destination	 During a call, tap [Blind Transfer] on the [Current] tab Enter the transfer destination's phone number, and then press. In Section 2. Go on-hook. In step 2, tapping [Transfer Cancel] before pressing Interpretation of the pression of the p
			call